

Functional requirements of 18W switching power supply

**IS 18VB-12**

Product application on LED light

**Size: 45x67x70mm**



Input Voltage:	
Rated Voltage	220 ~ 240Vac
Variation Range	200 - 264Vac
Input Frequency:	
Rated frequency	50/60Hz
Input frequency	47-63Hz
Input Current	0.5Amps max At any input voltage and rated, DC output rated load
Inrush Current	40 Amps Max. Cold start at 230Vac input, with rated load and 25 <sup>0</sup> C ambient
Ac Leakage Current	0.25mA max. at 264Vac input
Output	12V DC1.5A 18W
Input Plug	EU 2pin
Output plug	1.35x3.5x13MM inner positive
Output power cord	1200MM

**Size:**

Size, MM	L	B	b	H	l cord
	45	67	30	70	1200

